

AC22C-06




## REPLACEMENT

## REPLACE DRYER FROM MODULATOR

- (a) Using a 10 mm hexagon wrench, remove the cap from the modulator.
- (b) Remove the filter from the modulator.




(c) Using pliers, remove the dryer.



(d) Insert a new dryer into the modulator.

## NOTICE:


- Do not remove the dryer from a vinyl bag until inserting it into the modulator.
- Install the dryer with its 2 layered part faced upward to the modulator.



(e) Insert the filter into the modulator.

## **NOTICE:**

Install the filter with its protrusion faced downward to the modulator.



(f) Install the cap to the modulator.

(1) Apply compressor oil to the O-rings and screw part of the cap.

Compressor oil: ND-OIL 8 or equivalent

(2) Using a 10 mm hexagon wrench, install the caps.

Torque: 12.3 N-m (125 kgf-cm, 9 ft-lbf)

2000 MR2 (RM760U)

Author: Date: 1349